



BACnet is a registered trademark of ASHRAE. ASHRAE does not endorse, approve or test products for compliance with ASHRAE standards. Compliance of listed products to the requirements of ASHRAE Standard 135 is the responsibility of BACnet International. BTL is a registered trademark of BACnet International.

BACnet Testing Laboratories Product Listing

BACnet functionality in each Listed product has been successfully tested at a Recognized BACnet Testing Organization utilizing the industry standard BTL test suite and test policies that were current at the time it was tested. For Listings with multiple products, some products may have less functionality than is indicated by the Listing document. The PICS document provides information on the specific functionality of each product. Note that PICS documents on the BTL Listings site are provided by the manufacturer and are not independently verified by BTL.

Listing Information (BTL-31310)

Vendor		Listing Status
Fr. Sauter AG Im Surinam 55 4016 Basel Switzerland		Listed Product
Test Requirements	BACnet Protocol Revision	Date Tested
Requirements as of February 2024	Revision 24	January 2025

Product Name	Model Numbers	Version
EY-modulo 6 Building Controller	EY6AS60F011, EY6AS80F021	V2.1.2b4664

Device Profiles

Profile	Model Numbers
BACnet Building Controller (B-BC) BACnet Broadcast Management Device (B-BBMD) BACnet Secure Connect Hub (B-SCHUB) BACnet Lighting Device (B-LD)	All models

BIBBs Supported

Data Sharing	ReadProperty-A	DS-RP-A
	ReadProperty-B	DS-RP-B
	ReadPropertyMultiple-A	DS-RPM-A
	ReadPropertyMultiple-B	DS-RPM-B
	WriteProperty-A	DS-WP-A
	WriteProperty-B	DS-WP-B
	WritePropertyMultiple-B	DS-WPM-B
	Change Of Value-A	DS-COV-A
	Change Of Value-B	DS-COV-B
	Change Of Value Property-B	DS-COVP-B
	Change Of Value Unsubscribed-A	DS-COVU-A
	Change Of Value Unsubscribed-B	DS-COVU-B
	Lighting Output-B	DS-LO-B

Alarm and Event Notification	Notification-A	AE-N-A
	Notification Internal-B	AE-N-I-B
	Notification External-B	AE-N-E-B
	Acknowledge-B	AE-ACK-B
	Alarm Summary-B	AE-ASUM-B
	Enrollment Summary-B	AE-ESUM-B
	Information-B	AE-INFO-B
	Event Log-Internal-B	AE-EL-I-B
	Event Log-External-B	AE-EL-E-B
Configurable Recipient Lists-B	AE-CRL-B	

Scheduling	Internal-B	SCHED-I-B
	External-B	SCHED-E-B

Trending	Viewing and Modifying Trends Internal-B	T-VMT-I-B
	Viewing and Modifying Trends External-B	T-VMT-E-B
	Automated Trend Retrieval-B	T-ATR-B

Device Management	Dynamic Device Binding-A	DM-DDB-A
	Dynamic Device Binding-B	DM-DDB-B
	Dynamic Object Binding-B	DM-DOB-B
	DeviceCommunicationControl-B	DM-DCC-B
	TimeSynchronization-A	DM-TS-A
	TimeSynchronization-B	DM-TS-B
	UTCTimeSynchronization-A	DM-UTC-A
	UTCTimeSynchronization-B	DM-UTC-B
	ReinitializeDevice-B	DM-RD-B
	Backup and Restore-B	DM-BR-B
	Restart-A	DM-R-A
	Restart-B	DM-R-B
	List Manipulation-B	DM-LM-B
	Object Creation and Deletion-B	DM-OCD-B
	Automatic Time Synchronization-A	DM-ATS-A
	BBMD Configuration-B	NM-BBMD-C-B
	Foreign Device Registration-A	NM-FDR-A
Secure Connect Hub-B	NM-SCH-B	

Object Type Support

Analog Input	Analog Output	Analog Value
Binary Input	Binary Output	Binary Value
Calendar	Command	Device
Event Enrollment	Event Log	File
Lighting Output	Loop	Multi-State Input
Multi-State Output	Multi-State Value	Network Port
Notification Class	Positive Integer Value	Program
Pulse Converter	Schedule	Structured View
Trend Log		

Data Link Layer Options

Media	Options
BACnet/IP (Annex J)	BBMD Register as Foreign Device BACnet/IP, 'DIX' Ethernet
BACnet/SC	Hub

Character Set Support

ISO 10646 (UTF-8)
